



The TraceTek iServer is the simplest, easiest, most economical way to connect TraceTek Sensor Interface Modules (TT-SIM) to an Ethernet network and the Internet. When you type its name in a Web Browser, it serves customized TraceTek web pages that let you quickly and easily determine the status of your TraceTek leak detection system without any special software.

Getting started with the TraceTek iServer is simple and easy because it can take a dynamically assigned IP address from a DHCP server on your network. This DHCP client capability is a valuable and unique feature of the TraceTek iServer that makes it extremely easy and simple to start using this device on almost any Ethernet network. And, you can easily assign a static IP address to the iServer instead of a dynamic one, if necessary.

The TraceTek iServer connects up to 8 TT-SIM devices to an Ethernet Network with a standard network connector. The individual TT-SIM units are connected to the TraceTek iServer with a twisted pair, RS-485 two-wire network. The TT-SIM units can be mounted adjacent to the iServer or located thousands of feet away if necessary, but in most cases the iServer provides an opportunity to take advantage of the installed Ethernet and thereby minimize additional wiring costs.

When used in conjunction with a TTDM-128 Alarm Panel, the iServer can "see through" the TTDM and provide a separate remote status screen.

Since most leak detection systems are used for long term monitoring, the TraceTek iServer comes with a free companion Windows application. This companion application is installed on any Windows computer that is also connected to the LAN. The function of this software is to monitor all of the TraceTek iServers in your facility for leak detections or other alarm conditions. If an alarm condition is detected by one of the TT-SIM units, the iServer informs the monitor program and the monitor program will immediately send an email notification to up to five recipients. The recipients can be pagers, cell phones or normal email accounts.

If a leak in one of your facilities is detected, the right people will be informed within a few seconds. They can then use any PC with access to the LAN and use a standard Web Browser to get detailed status information including the leak location to the nearest meter.

- Connects TT-SIM units to an Ethernet network and the Internet.
- Replaces dedicated wiring and PC's.
- Includes Windows based monitor and email notification to pager and mobile phones.
- Use any browser to view status, leak locations, etc.
- Simple industry standard connectivity to LAN and WAN using DHCP and HTTP protocol.
- 24V DC power
- Password protected.
- DIN Rail Mounting.



**TraceTek**      **Midco Terminal**

No.	SQL Classid	Classid ID	Current Status	Last (Pct)
1	1	Pipe Section 1	NORMAL	...
2	1	Valve Manifold	LEAK	...
3	4	Task 1 Pump	NORMAL	...
4	5	Task 2 Pump	PROBLE	...
5	...	...	...	...
6	1	Auxiliary tank	NORMAL	...
7	3	val 1 work	LEAK	...
8	...	...	...	...

    
      
      

Click on device or cell to modify SQL configuration. Password: 1234567890123456

Ordering Information	Catalog Number	Description
	TT-EIS-2B	TT-iServer SIM to Ethernet bridge, 24VDC

